

AZ928

High Speed Telco Satellite Demodulator

Azimuth Product Family

AZIMUTH

SERIES

Description

The AZ928 High Speed Telco Satellite Demodulator is to be used in pair with the High Speed Telco Modulator AZ128 to establish fixed rate 155.52 Mbit/s point to point satellite links. The equipment interconnects seamlessly with standard terrestrial SDH / SONET networks via a STM-1 or OC-3 interface. The satellite transmission can be operated on 54 MHz or 72 MHz transponders.

The modulation is fully compliant with the DVB-S2 standard and provides exceptional power and bandwidth efficiency. When activated on the modulator, the linear and non- linear predistortion option Equalink™ provides an additional link margin improvement of up to 2dB. An adaptive channel equalizer compensates linear link distortion.

In standard configuration the AZ928 operates with a 16APSK modulation scheme.

The AZ928 is equipped with a dual L-band input (950-2150 MHz). The standard L-band input has the option to deliver 10 MHz over the L-band inter-facility link to the LNB. Optionally one L-band input can be replaced by an IF (50-180 MHz) input. At the output the signal is converted to an electrical G.703 or an optical single or multi mode signal.

Key features

- 155 Mbit/s transmission on a 54 or 72 MHz satellite transponder
- 16 APSK modulation schemes
- Electrical G.703 and optical interfaces
- Full remote control and monitoring capability that easily integrates with market leading network management systems

Main advantages

- Highest link availability: the AZ928 provides the most efficient link budget available on the market
- Lowest operational costs: full SDH/SONET link in a 54 MHz transponder
- Lowest infrastructure cost: the high power efficiency requires smaller antennas

Applications

- Cable restoration
- Cable back up
- Disaster recovery
- Business continuity
- Internet backbone
- WAN interconnection

Related products

AZ128 High Speed Telco Satellite Modulator

AZ720 Downconverter

AZ730 Up & Downconverter

AZ290 1+1 Demodulator Redundancy Switch

Related Documents

White paper "Equalizing and Predistortion: the Equalink concept"



SHAPING THE FUTURE OF SATELLITE COMMUNICATIONS

Specifications - AZ928(R6)

Input interface

Dual L-band input (default)

- Connector
 - Return loss
 - Level
 - Frequency
 - Adjacent signal
- 2 x F-type (F), 75 ohms
 > 7 dB
 -65/-25dBm
 950 - 2150 MHz
 < (Co+7) dBm/Hz
 where Co = signal level density

IF-band input (optional, replaces one L-band input)

- Connector
 - Return loss
 - Level
 - Frequency
 - Adjacent signal
- BNC (F) - 75 ohms
 > 15 dB
 -55 to -15 dBm
 50 - 180 MHz
 < (Co+7) dBm/Hz
 where Co = signal level density

LNB power and control

- max. current
 - voltage
- 350 mA (on selected IFL input)
 11,5 -14 V (Vertical polarization)
 16-19V (Horizontal polarization)
 & additional 22 kHz +/- 4KHz (band selection according to universal LNB for Astra satellites & DiSEqC command transmission)
- 10 MHz reference

Reference interfaces

External 10.0 MHz reference input (optional):

- Connector
 - Input level
 - Output level
- BNC (F) – 50 ohms
 -3dBm up to 7dBm
 +7dBm

LNB reference frequency output (optional, only available with L-band)

- frequency
 - stability
 - warm up time
 - ageing
- 10 MHz
 ±5x10-8 over 0°C to 65°C
 5 min (±100 ppb)
 ±15 ppb/day
 ± 300 ppb/year

Demodulation

Satellite baud rate

Modul.	FEC	Rate (Mbaud)
16APSK	8/9	44.14
16APSK	9/10	43.60

BER performance for QEF

Config	EN302307 Simulations(**)	Measured performance (*)	
		Es/No	Es/No
16APSK- 8/9	12.89	13.3	
16APSK- 9/10	13.13	13.6	

(*) Measured over Ku-band (with LNB type : SMW PLL) in linear channel

(**) REF BER=1E-10

Synchronisation:

- Carrier acquisition range ±8.75 MHz max
- Clock acquisition range ± 200 ppm max.
- Average acquisition time < 3 sec, 90% probability, carrier freq. offset < ± 2.5 MHz ptp and BER<5E-8

Output interfaces

Electrical G.703

- Connector
 - Coupling
 - Line coding
 - Level
- BNC female @ 75 ohms
 transformer
 CMI
 1 Vptp (nom.)

Optical multi mode

- Connector
 - Fiber
 - Spectral width
 - Transmit power
 - Received power
- SC
 1300 nm multi mode
 62.5/125 mm
 58 nm rms (typ.)
 -14 dBm (max.)
 -20 dBm (min.)
 -14 dBm (max.)
 -30 dBm (min.)

Optical single mode

- Connector
 - Fiber
 - Spectral width
 - Transmit power
 - Received power
 - Interface rate: 155.52 Mbit/s +/- 20 ppm
- SC
 1300 nm single mode
 7.7 nm rms (max.)
 -8 dBm (max.)
 -15 dBm (min.)
 -8 dBm (max.)
 -31 dBm (min.)

Internal Reference frequency

- High Stability (optional)
 Stability ±5x10-8 over 0°C to 70°C
 Ageing: ± 15 ppb/day
 ± 300 ppb/year
- Very High Stability (optional)
 Stability ±2x10-9 over 0°C to 65°C
 Ageing: ± 0.5 ppb/day
 ± 500 ppb/10 year

Generic

Monitor and control interfaces

- Web based GUI
- Diagnostics report, alarm log
- RMCP over TCP-IP/UDP and RS232/RS485
- SNMP v2c

Alarm interface

- Electrical dual contact closure alarm contacts
- Connector 9-pin sub-D (F)
- Logical interface and general device alarm

Physical

- Very compact: 1RU, width: 19", depth 51 cm, 6 kg
- Power supply: 90-130 & 180-260 Vac, 105 VA, 47-63 Hz
- Temperature
 - Operational: 0°C to 40°C
 - Storage: -40 to +70°C
- Humidity: 5% to 85% non-condensing
- CE label

Ordering information

AZ928 High Speed Telco Satellite Demodulator	Order n°
Default Configuration	
DVB-S2 16 APSK demodulator with STM-1/OC3 interface, SNMP Input interface : L-band (950-2150 MHz)	
AZ928	
Configuration options¹	
Category Max. 1 option per category	
Input Interface	L-band
	IF + L-band
AJ-03	
Additional options¹	
Category Max. 1 option per category	
10 MHz reference In/Out	High stability
	Very high stability
GR-01	GR-02

¹ Other configurations and options such as 10 MHz on L-band for LNB are available on request.
 Contact your sales representative for details (sales@newtec.eu).

Europe

Tel: +32 3 780 65 00

Fax: +32 3 780 65 49

North-America

Tel: +1 203 323-0042

Fax: +1 203 323-8406

South-America

Tel: +55 (11) 2092 6220

Fax: +55 (11) 2093 3756

Asia-Pacific

Tel: +65 6777 22 08

Fax: +65 6777 08 87

China

Tel: +86 10-823 18 730

Fax: +86 10-823 18 731

MENA

Tel: +971 4 390 18 78

Fax: +971 4 368 67 68

Africa

Tel: +27 11 640 2745

mbr@newtec.eu